

Subspace Methods: Eigenvalue Method and MUSIC

ECE 6279: Spatial Array Processing
Spring 2007
Lecture 19
2/28/07

Prof. Aaron D. Lanterman

School of Electrical & Computer Engineering
Georgia Institute of Technology
AL: 404-385-2548
<lanterma@ece.gatech.edu>

Copyright 2007 Aaron Lanterman



Where We Are in J&D

- Section 7.3



Copyright 2007 Aaron Lanterman



Eigenexpansions

- Write correlation matrix in terms of its eigensystem:

$$\mathbf{R}_y = \sum_{m=1}^M \lambda_m \mathbf{v}_m \mathbf{v}_m^H$$

$$\mathbf{R}_y^{-1} = \sum_{m=1}^M \lambda_m^{-1} \mathbf{v}_m \mathbf{v}_m^H$$



Copyright 2007 Aaron Lanterman



Eigensystem for a One-Signal Case (1)

- Think about one signal in white noise:

$$\mathbf{R}_y = A_s^2 \mathbf{e}(\vec{k}^0) \mathbf{e}^H(\vec{k}^0) + \sigma_n^2 \mathbf{I}$$

- Let $\mathbf{v}_1 = \mathbf{e}(\vec{k}^0) / \sqrt{M}$
- Let $\mathbf{v}_2, \dots, \mathbf{v}_M$ be any set of orthogonal vectors orthogonal to \mathbf{v}_1

$$\mathbf{R}_y = M A_s^2 \mathbf{v}_1 \mathbf{v}_1^H + \sum_{m=1}^M \sigma_n^2 \mathbf{v}_m \mathbf{v}_m^H$$

$$\lambda_1 = M A_s^2 + \sigma_n^2, \lambda_2, \dots, \lambda_M = \sigma_n^2$$



Copyright 2007 Aaron Lanterman



Eigensystem for a One-Signal Case (2)

$$\begin{aligned} \mathbf{R}_y &= A_s^2 \mathbf{e}(\vec{k}^0) \mathbf{e}^H(\vec{k}^0) + \sigma_n^2 \mathbf{I} \\ &= M A_s^2 \mathbf{v}_1 \mathbf{v}_1^H + \sum_{m=1}^M \sigma_n^2 \mathbf{v}_m \mathbf{v}_m^H \\ \lambda_1 &= M A_s^2 + \sigma_n^2, \lambda_2, \dots, \lambda_M = \sigma_n^2 \end{aligned}$$

- If we had \mathbf{R}_y exactly, we could find $\mathbf{e}(\vec{k}^0)$ without knowing anything about the array!



Copyright 2007 Aaron Lanterman



Eigensystem for a Two-Signal Case

- Two signals in white noise: $\mathbf{R}_y = A_1^2 \mathbf{e}(\vec{k}_1^0) \mathbf{e}^H(\vec{k}_1^0) + A_2^2 \mathbf{e}(\vec{k}_2^0) \mathbf{e}^H(\vec{k}_2^0) + \sigma_n^2 \mathbf{I}$

- Can express steering vectors as linear combinations of the two largest eigenvalues $\mathbf{v}_1, \mathbf{v}_2$

$$\mathbf{e}(\vec{k}_1^0) = t_{11} \mathbf{v}_1 + t_{21} \mathbf{v}_2$$

$$\mathbf{e}(\vec{k}_2^0) = t_{12} \mathbf{v}_1 + t_{22} \mathbf{v}_2$$



Copyright 2007 Aaron Lanterman



Subspace Decompositions

$$\begin{bmatrix} \mathbf{e}(\vec{k}_1^0) & \mathbf{e}(\vec{k}_2^0) \end{bmatrix} = \underbrace{\begin{bmatrix} \mathbf{v}_1 & \mathbf{v}_2 \end{bmatrix}}_{\mathbf{V}_{s+n}} \underbrace{\begin{bmatrix} t_{11} & t_{12} \\ t_{21} & t_{22} \end{bmatrix}}_{\mathbf{T}}$$

For $N_s < M$ signals, we have

$\mathbf{v}_1, \dots, \mathbf{v}_{N_s}$ **signal+noise subspace**

$\mathbf{v}_{N_s+1}, \dots, \mathbf{v}_M$ **noise subspace**

Can never really know

\mathbf{T} , so focus on **noise subspace**



Copyright 2007 Aaron Lanterman



Decomposing MVDR

$$\begin{aligned} P^{MV}(\vec{k}) &\equiv \left[\mathbf{e}^H(\vec{k}) \mathbf{R}_y^{-1} \mathbf{e}(\vec{k}) \right]^{-1} \\ &= \left[\sum_{i=1}^M \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2 \right]^{-1} \end{aligned}$$

$$\underbrace{\sum_{i=1}^{N_s} \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2}_{\text{signal+noise terms}} + \underbrace{\sum_{i=N_s+1}^M \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2}_{\text{noise terms}}$$

Copyright 2007 Aaron Lanterman



Considering the Signal+Noise Terms

- How can we get more “dramatic” peaks from the MVDR spectrum?

$$\sum_{i=1}^{N_s} \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2 + \sum_{i=N_s+1}^M \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2$$

- When $\mathbf{e}(\vec{k})$ corresponds to an actual signal, inner products of it with signal+subspace eigenvectors are large
- This makes the term above not as small as it could be, so MVDR power (reciprocal above term) is not as big as it could be

Copyright 2007 Aaron Lanterman



Considering the Noise Terms

- How can we get more “dramatic” peaks from the MVDR spectrum?

$$\sum_{i=1}^{N_s} \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2 + \sum_{i=N_s+1}^M \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2$$

- When $\mathbf{e}(\vec{k})$ corresponds to an actual signal, inner products of it with noise eigenvectors are small (ideally zero)
- Reciprocals of small numbers are big!

Copyright 2007 Aaron Lanterman



Eigenvalue Method

~~$$\sum_{i=1}^{N_s} \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2 + \sum_{i=N_s+1}^M \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2$$~~

$$P^{EV}(\vec{k}) \equiv \left[\sum_{i=N_s+1}^M \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2 \right]^{-1} = \left[\mathbf{e}^H(\vec{k}) \mathbf{R}_{EV}^{-1} \mathbf{e}(\vec{k}) \right]^{-1}$$

where $\mathbf{R}_{EV}^{-1} = \sum_{i=N_s+1}^M \lambda_i^{-1} \mathbf{v}_i \mathbf{v}_i^H$

Copyright 2007 Aaron Lanterman



MUSIC (1)

$$P^{EV}(\vec{k}) \equiv \left[\sum_{i=N_s+1}^M \lambda_i^{-1} \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2 \right]^{-1}$$

- If $\mathbf{K}_n = \sigma_n^2 \mathbf{I}$, noise subspace eigenvalues are theoretically σ_n^2

$$P^{MUSIC}(\vec{k}) \equiv \left[\sum_{i=N_s+1}^M \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2 \right]^{-1}$$

Copyright 2007 Aaron Lanterman




MUSIC (2)

$$P^{MUSIC}(\vec{k}) = \left[\mathbf{e}^H(\vec{k}) \mathbf{R}_{MUSIC}^{-1} \mathbf{e}(\vec{k}) \right]^{-1}$$

where $\mathbf{R}_{MUSIC}^{-1} = \sum_{i=N_s+1}^M \mathbf{v}_i \mathbf{v}_i^H$

- “Whitens” noise subspace
- “Flattens” background
- “Pulls” signals out of noisy background



Copyright 2007 Aaron Lanterman



Modified Correlation Matrices

$$\mathbf{R}_{EV}^{-1} = \sum_{i=N_s+1}^M \lambda_i^{-1} \mathbf{v}_i \mathbf{v}_i^H \quad \mathbf{R}_{EV} = \sum_{i=N_s+1}^M \lambda_i \mathbf{v}_i \mathbf{v}_i^H$$

$$\mathbf{R}_{MUSIC}^{-1} = \sum_{i=N_s+1}^M \mathbf{v}_i \mathbf{v}_i^H \quad \mathbf{R}_{MUSIC} = \sum_{i=N_s+1}^M \mathbf{v}_i \mathbf{v}_i^H$$

- Can use these modified correlations in other algorithms (linear prediction, etc.)
- But... almost always used in MVDR



Copyright 2007 Aaron Lanterman



Special Cases (1)

- EV doesn't change the eigenvalues it keeps
- Hence, it reduces to MVDR if we take the number of sources to be zero



Copyright 2007 Aaron Lanterman



Special Cases (2)

- Remember Pisarenko method:

Look for valleys in: $\left| \mathbf{e}^H(\vec{k}) \mathbf{v}_{\min} \right|$

Look for peaks in: $\left| \mathbf{e}^H(\vec{k}) \mathbf{v}_{\min} \right|^{-1}$

- Like MUSIC method with $N_s = M - 1$

$$P^{MUSIC}(\vec{k}) \equiv \left[\sum_{i=N_s+1}^M \left| \mathbf{e}^H(\vec{k}) \mathbf{v}_i \right|^2 \right]^{-1}$$



Copyright 2007 Aaron Lanterman



Good Properties of EV and Music

- **Good resolution properties overall**
- **In white Gaussian noise:**
 - Resolution increases without limit with increasing SNR
 - Peak locations “asymptotically unbiased”
- **In non-white noise:
Resolution still good, but has limits**
 - Peak locations usually biased




Copyright 2007 Aaron Lanterman



Drawbacks of EV and MUSIC

- **Neither EV or MUSIC are very robust to modeling assumptions**
 - Why conventional BF is still popular
- **MUSIC very sensitive to assumption of number of sources due to flattening the eigenvalues**
 - EV also sensitive, but not as sensitive
- **Correlated sources badly mess up subspace methods (see p. 389)**



Copyright 2007 Aaron Lanterman

