

Time Averaging

ECE 6279: Spatial Array Processing
Fall 2013
Lecture 12

Prof. Aaron D. Lanterman

School of Electrical & Computer Engineering
Georgia Institute of Technology
AL: 404-385-2548
<lanterma@ece.gatech.edu>

Copyright 2013 Aaron Lanterman



Average Beamformer Output

- Average power of beamformer output over time

$$\begin{aligned}\hat{z} &= \frac{1}{L} \sum_{l=0}^{L-1} |z(l)|^2 = \frac{1}{L} \sum_{l=0}^{L-1} |\mathbf{e}^H(\vec{k}) \mathbf{W} \mathbf{y}(l)|^2 \\ &= \frac{1}{L} \sum_{l=0}^{L-1} \mathbf{e}^H(\vec{k}) \mathbf{W} \mathbf{y}(l) \mathbf{y}^H(l) \mathbf{W}^H \mathbf{e}(\vec{k}) \\ &= \mathbf{e}^H(\vec{k}) \mathbf{W} \left[\frac{1}{L} \sum_{l=0}^{L-1} \mathbf{y}(l) \mathbf{y}^H(l) \right] \mathbf{W}^H \mathbf{e}(\vec{k})\end{aligned}$$

Copyright 2013 Aaron Lanterman



Where We Are (and Aren't) in J&D

- Inspired by Section 4.9.1

Copyright 2013 Aaron Lanterman



Under the Stochastic Model

$$\hat{z} = \mathbf{e}^H(\vec{k}) \mathbf{W} \hat{\mathbf{R}}_y \mathbf{W}^H \mathbf{e}(\vec{k})$$

$$\text{where } \hat{\mathbf{R}}_y = \frac{1}{L} \sum_{l=0}^{L-1} \mathbf{y}(l) \mathbf{y}^H(l)$$

- Under the stochastic signal model, $\hat{\mathbf{R}}_y$ is the unconstrained maximum-likelihood estimate of the correlation matrix of a Gaussian random vector \mathbf{y}

Copyright 2013 Aaron Lanterman



Improvement from Time Averaging

$$\hat{\mathbf{R}}_y \rightarrow \mathbf{R}_y = E[\underline{\mathbf{y}}\underline{\mathbf{y}}^T] \text{ as } L \rightarrow \infty$$

- If snapshots are independent, variance of estimate improves as O(1/L), standard deviation improves as O(1/sqrt(L))**
- Can't make L too big if the sources are moving!**

Copyright 2013 Aaron Lanterman



Outer Product of Steering Vectors

- For linear array**

$$\gamma = k \sin(\phi) \cos(\theta) d \\ = \frac{2\pi}{\lambda} \sin(\phi) \cos(\theta) d$$

$$= \begin{bmatrix} 1 & e^{j\gamma} & \dots & e^{-j(M-1)\gamma} \\ e^{j\gamma} & \vdots & & \\ \vdots & & \ddots & \vdots \\ e^{j(M-1)\gamma} & \dots & e^{j\gamma} & 1 \end{bmatrix} \begin{bmatrix} 1 & e^{-j\gamma} & \dots & e^{-j(M-1)\gamma} \\ e^{-j\gamma} & 1 & \ddots & \vdots \\ \vdots & \ddots & \ddots & e^{-j\gamma} \\ e^{-j(M-1)\gamma} & \dots & e^{-j\gamma} & 1 \end{bmatrix}$$

Copyright 2013 Aaron Lanterman



Linear Array, Single Plane Wave

- Assuming no noise**

$$\mathbf{y}(l) = s(l) \exp\left(-j \frac{M-1}{2}\gamma\right) \exp\begin{bmatrix} 0 \\ j\gamma \\ \vdots \\ j(M-1)\gamma \end{bmatrix}$$

$$\mathbf{y}(l)\mathbf{y}^H(l) = |s(l)|^2 \exp\begin{bmatrix} 0 & -j\gamma & \dots & -j(M-1)\gamma \\ j\gamma & 0 & \ddots & \vdots \\ \vdots & \ddots & \ddots & -j\gamma \\ j(M-1)\gamma & \dots & j\gamma & 0 \end{bmatrix}$$

Copyright 2013 Aaron Lanterman



Toeplitz Structure of Est. Correlation

$$\hat{\mathbf{R}}_y = \frac{1}{L} \sum_{l=0}^{L-1} \mathbf{y}(l)\mathbf{y}^H(l)$$

- $\hat{\mathbf{R}}_y$ is Toeplitz since a sum of Toeplitz matrices is Toeplitz**
- Remember we are assuming no noise**

Copyright 2013 Aaron Lanterman



Convergence to True Correlation

$$\hat{\mathbf{R}}_y \rightarrow E\left[\underline{s}^2\right] \exp \begin{bmatrix} 0 & -j\gamma & \cdots & -j(M-1)\gamma \\ j\gamma & 0 & \ddots & \vdots \\ \vdots & \ddots & \ddots & -j\gamma \\ j(M-1)\gamma & \cdots & j\gamma & 0 \end{bmatrix}$$

as $L \rightarrow \infty$



Copyright 2013 Aaron Lanterman

Linear Array, Two Plane Waves

- Again assuming no noise

$$\mathbf{y}(l) = s_1(l) \exp\left(-j \frac{M-1}{2} \gamma_1\right) \exp \begin{bmatrix} 0 \\ j\gamma_1 \\ \vdots \\ j(M-1)\gamma_1 \\ 0 \\ j\gamma_2 \\ \vdots \\ j(M-1)\gamma_2 \end{bmatrix}$$

Copyright 2013 Aaron Lanterman

Two Signals

$$\mathbf{y}(l)\mathbf{y}^H(l) = |s_1(l)|^2 \begin{bmatrix} 1 & e^{-j\gamma_1} & \cdots & e^{-j(M-1)\gamma_1} \\ e^{j\gamma_1} & 1 & \ddots & \vdots \\ \vdots & \ddots & \ddots & e^{-j\gamma_1} \\ e^{j(M-1)\gamma_1} & \cdots & e^{j\gamma_1} & 1 \end{bmatrix}$$

$+|s_2(l)|^2$ [same but with γ_2]

+crossterms!!!



Copyright 2013 Aaron Lanterman

Crossterms (1)

$$s_1(l)e^{-j\frac{M-1}{2}\gamma_1} \begin{bmatrix} 1 \\ e^{j\gamma_1} \\ \vdots \\ e^{j(M-1)\gamma_1} \end{bmatrix} s_2^*(l)e^{j\frac{M-1}{2}\gamma_2} \begin{bmatrix} 1 \\ e^{-j\gamma_2} \\ \vdots \\ e^{-j(M-1)\gamma_2} \end{bmatrix}^T$$

$$+s_2(l)e^{-j\frac{M-1}{2}\gamma_2} \begin{bmatrix} 1 \\ e^{j\gamma_2} \\ \vdots \\ e^{j(M-1)\gamma_2} \end{bmatrix} s_1^*(l)e^{j\frac{M-1}{2}\gamma_1} \begin{bmatrix} 1 \\ e^{-j\gamma_1} \\ \vdots \\ e^{-j(M-1)\gamma_1} \end{bmatrix}^T$$

Copyright 2013 Aaron Lanterman

Crossterms (2)

$$\exp \left[\begin{array}{cccc} 0 & -j\gamma_2 & \dots & -j(M-1)\gamma_2 \\ j\gamma_1 & j(\gamma_1 - \gamma_2) & \ddots & \vdots \\ \vdots & \ddots & \ddots & j[(M-2)\gamma_1 - (M-2)\gamma_2] \\ j(M-1)\gamma_1 & \dots & j[(M-1)\gamma_1 - (M-2)\gamma_2] & j(M-1)(\gamma_1 - \gamma_2) \\ & + s_2(l)s_1^*(l)e^{-j\frac{(M-1)}{2}(\gamma_2 - \gamma_1)} & \times & \\ 0 & -j\gamma_1 & \dots & -j(M-1)\gamma_1 \\ j\gamma_2 & j(\gamma_2 - \gamma_1) & \ddots & \vdots \\ \vdots & \ddots & \ddots & j[(M-2)\gamma_2 - (M-2)\gamma_1] \\ j(M-1)\gamma_2 & \dots & j[(M-1)\gamma_2 - (M-2)\gamma_1] & j(M-1)(\gamma_2 - \gamma_1) \end{array} \right]$$

Copyright 2013 Aaron Lanterman



Crossterm Matrix Elements

- i*th diagonal element of crossterm matrix given by

$$2 \operatorname{Re} \left\{ s_1(l)s_2^*(l) \exp \left(-j \frac{M-1}{2} [\gamma_1 - \gamma_2] \right) \exp(j[\gamma_1 - \gamma_2]i) \right\}$$

$$= 2 |s_1(l)s_2^*(l)| \cos \left([\gamma_1 - \gamma_2] \left[i - \frac{M-1}{2} \right] + \angle \{ s_1(l)s_2^*(l) \} \right)$$



Copyright 2013 Aaron Lanterman



Intersignal Coherence

$$\frac{1}{L} \sum_{l=0}^{L-1} s_1(l)s_2^*(l) \rightarrow \underbrace{E[s_1 s_2^*]}_{\text{Intersignal coherence}}$$

- Incoherent signals have an intersignal coherence of zero
- Coherence suggests multipath effects



Copyright 2013 Aaron Lanterman

